

**CALL SWITCHES
WITH VOLUME CONTROL
DL-24CB, DL-24ECB**

FEATURES:

- FITS A SINGLE-GANG ELECTRICAL BOX
- BUILT-IN VOLUME CONTROL
- BRUSHED STAINLESS STEEL WALL PLATE
- BLACK "CALL" BUTTON FOR NORMAL CALL
- RED "CALL" BUTTON FOR EMERGENCY CALLS (DL-24ECB)



DESCRIPTION:

The DL-24CB (Call Switch) and the DL-24ECB (Emergency/Normal Call Switch with Volume Control) are designed to be used with the DL-24 and DL-24EXP Industrial/School Intercom Units. The DL-24ECB emergency button transposes a single button press into the four switch closures required to generate an "Emergency" class of service call.

SPECIFICATIONS:

MOUNTING

Call button mounts in a single gang electrical box using two screws.

SWITCH (DL-24CB)

Single pole momentary pushbutton

SWITCHES (DL-24ECB)

Single pole momentary pushbutton "Normal Call" black cap

Single pole momentary pushbutton with red cap and electronic pulse generator "Emergency Call"

ENVIRONMENT:

Suitable for indoor installations

HOUSING AND FINISH

Brushed stainless steel single gang wall plate with black screen printed text.

DIMENSIONS AND WEIGHT:

4.5" (11.43 cm) W x 2.75" (6.99 cm) H x 2.125" (5.4 cm) D

Weight: 1.0 lb. (.45 Kg)

ARCHITECTS' AND ENGINEERS' SPECIFICATIONS MODEL DL-24CB CALL SWITCH WITH VOLUME CONTROL DL-24ECB EMERGENCY/NORMAL CALL SWITCH WITH VOLUME CONTROL

DL-24CB

The call switch shall be a momentary pushbutton switch with a .5" square black plastic cap mounted on a brushed stainless steel plate. A screwdriver set volume control shall be provided to allow audio level adjustment of externally connected 45-ohm speakers. The unit shall be compatible with single gang electrical boxes.

Dimensions shall be 4.5" (11.43 cm) W x 2.75" (6.99 cm) H x 2.125" (5.4 cm) D and the unit shall weigh 1.0 lbs. (.45 Kg). The Call switch with volume control shall be Clarity Model Number DL-24CB.

DL-24ECB

The "Normal" call switch shall be a momentary pushbutton style switch with a .5" square Black plastic cap. The "Emergency" call switch shall be a momentary pushbutton style switch with a .5" square Red plastic cap. A pulse generator shall be provided as part of the call station to transpose a single press of the emergency button to four closures. The call station shall be line powered. A screwdriver set volume control shall be provided to allow audio level adjustment of externally connected 45-ohm speakers.

The unit shall be compatible with single gang electrical boxes. Dimensions shall be 4.5" (11.43 cm) W x 2.75" (6.99 cm) H x 2.125" (5.4 cm) D and the unit shall weigh 1.0 lbs. (.45 Kg). The Emergency Call station with volume control shall be Clarity Model Number DL-24ECB.

Limited Warranty

Clarity warrants its products to be free from defects in materials and workmanship under conditions of normal use and service for a period of one year from the date of shipment. The obligation under this warranty shall be limited to the replacement, repair or refund of any such defective device within the warranty period, provided that:

1. inspection by Clarity indicates the validity of the claim,
2. the defect is not the result of damage, misuse, or negligence after the original shipment,
3. the product has not been in any way repaired by others and that factory sealed units are unopened.
(A service charge plus parts and labor will be applied to units defaced or physically damaged).
4. freight charges for the return of products to Clarity are prepaid,
5. all units "out of warranty" are subject to a service charge. The service charge will cover minor repairs
(major repairs will be subject to additional charges for parts and labor).

This warranty is in lieu of and excludes all other warranties expressed or implied, and in no event shall Clarity be liable for any anticipated profits, consequential damages, loss of time or other losses incurred by the buyer in connection with the purchase, operation or use of the product.

This warranty specifically excludes damage incurred in shipment. In the event a product is received in damaged condition, the carrier should be notified immediately. Claims for such damage should be filed with the carrier involved in accordance with the F.O.B. point.